



Daffodil International University
Faculty of Science & Information Technology
Department of Computer Science and Engineering
Final Examination, Spring 2024
Course Code: CSE 331 , Course Title: Compiler Design
Level: 4 Term: 1 Batch: 59

Time: 2:00 Hrs

Total Marks: 40

Answer ALL Questions

[The figures in the right margin indicate the full marks and corresponding course outcomes. All portions of each question must be answered sequentially.]

1.		$\text{Expr} \rightarrow \text{Expr} + \text{Term} \mid \text{Term}$ $\text{Term} \rightarrow \text{Term} * \text{Factor} \mid \text{Factor}$ $\text{Factor} \rightarrow (\text{Expr}) \mid \text{id}$		CO2
	a)	Convert the given left-recursive grammar into right-recursive grammar.	[3]	
	b)	Find FIRST() and FOLLOW() for the right-recursive grammar.	[3]	
	c)	Check whether the right-recursive grammar is LL(1) parser or not	[4]	
2.	a)	Produce Canonical Table from the following grammar $S \rightarrow L = R$ $L \rightarrow * R \mid \text{id}$ $R \rightarrow L$	[6]	CO2
	b)	Suppose that the input string is $\text{id} = * \text{id}$. Find whether the input string is accepted or rejected for the given (2a) LR(0) Parser.	[4]	
3.	a)	Convert the following arithmetic expression into various intermediate representations: $((\text{rate} * (\text{vat} + \text{tax})) - ((\text{cost} * \text{tax}) + (\text{revenue} + (\text{vat} + \text{tax}))))$ a) Represent the expression using Three Address Code. b) Represent the expression using Quadruples. c) Implement a Triples data structure to represent the expression. d) Construct the syntax tree for the expression. e) Create a Directed Acyclic Graph (DAG) for the expression.	[10]	CO3

4.	a)	Consider the following three address codes and answer the questions.	[10]	CO3
		<div style="display: flex; justify-content: space-between;"> <div style="width: 48%;"> <p>1. $x := 5$</p> <p>2. $y := 10$</p> <p>3. $z := x + y$</p> <p>4. $t1 := z - 2$</p> <p>5. $x := t1 + y$</p> <p>6. if $x < y$ goto 7.</p> <p>7. $t2 := x * y$</p> <p>8. $y := 15$</p> <p>9. $z := z + y$</p> <p>10. $w := x - y$</p> <p>11. if $t1 = 0$ goto 17</p> <p>12. $w := x + y$</p> <p>13. $t3 := y - z$</p> <p>14. $z := w - t3$</p> <p>15. if $z < w$ goto 3</p> <p>16. $z := x + y$</p> <p>17. output z</p> <p>18. output w</p> </div> <div style="width: 48%;"> <p>19. $x := 10$</p> <p>20. $y := 15$</p> <p>21. $a := x * y$</p> <p>22. $t1 := a + 3$</p> <p>23. $x := t1 + y$</p> <p>24. if $x < y$ goto 25</p> <p>25. $t2 := x + y$</p> <p>26. $y := 15$</p> <p>27. $a := a + y$</p> <p>28. $b := x - y$</p> <p>29. if $t1 = 0$ goto 35</p> <p>30. $b := x * y$</p> <p>31. $t3 := y - z$</p> <p>32. $a := b - t2$</p> <p>33. if $b < b$ goto 21</p> <p>34. $a := x + y$</p> <p>35. output a</p> <p>36. output b</p> </div> </div>		
		<p>a) Identify the lines of code that serve as leader instructions according to leader selection rule 2.</p> <p>b) Identify the lines of code that serve as leader instructions according to leader selection rule 3.</p> <p>c) Identify the lines which are selected as leader instruction according to both selection rule 2 and 3.</p> <p>d) Draw the control flow graph (CFG) for the given three-address code.</p> <p>e) Explain how the Constant Propagation optimization technique could be implemented on this code, mentioning the lines where this optimization can be applied.</p>		